

CGAS-AP-CO Transmitter

Analog Transmitter with Electrochemical Carbon Monoxide (CO) Sensor (standard range)

Dimensions:	Size	4.9 x 4.9 x 2 in / 124.9 x 124.9 x 50 mm
	Weight	286 g / 10 oz
Construction:		Polycarbonate, white, low profile
Sensor: Type		Electrochemical
Life Span		Approximately 3 years (application dependent)
Complies With		UL2075, 2 nd Edition, Standard for Gas and Vapour Detectors and Sensors
Gases Detected:		Carbon Monoxide (CO)
Sensor Range:		0 – 200 ppm (standard)
System Power:		3-wire: VDC: 16-30 VDC, 3-Watts, Class 2 4-wire: VAC: 12-27 VAC, 3-VA, Class 2
		Peak Power Draw: 1.68 watts* *add 0.15 watts for relay if installed
Operating Temperature:		0°C to +40°C (32°F to 104°F)
Operating Humidity:		15 to 90% non-condensing
Indicators:		LCD digital display, 2 line x 16 character, backlit
Signal:		Current: Linear 4-20 mA (maximum 216 ohm load, wiring plus termination resistor @ 12VDC) Maximum 316 ohm load, wiring plus termination resistor @ 12VAC
Relay (Option -RLY):		1 SPDT relay rated 30 volts, 2 amp max, Power Draw: 0.15 watts
Relay and Audible (Option -RBZ):		1 SPDT dry contact relay rated 30 volts, 2 amp max Internal buzzer, rated 90 dB @ 10 cm / 4 in, enable/disable
Audible:		none
Minimum Detection:		2 ppm (with regular calibration maintenance of sensor)
Accuracy:		<1ppm
Repeatability:		< ±3% CO equivalent
Sensitivity Drift:		<5 % per year
Response Time (T₉₀):		<30 seconds
Resolution:		Display resolution 1 ppm Sensor resolution: <1 ppm
Warm Up Time:		3 minutes after power up (to full operation)
Cross Sensitivity:		H ₂ @1000 ppm = <35ppm, NO@50ppm = <10ppm, C ₂ H ₆ O@200ppm = <1ppm, CL ₂ @15 = <1ppm, C ₂ H ₄ @100ppm = <96ppm, C ₂ H ₂ @100ppm = <90ppm
Safety:		Automatic resetting thermal overload fuse (reset capabilities to 500 times)
Wiring:		VDC or ground referenced VAC, 3-conductor shielded 18 awg stranded VAC 4-conductor shielded 18 awg stranded
Sensor Mounting:		Breathing Zone - slightly lighter than air 4 to 6 ft (1.2 to 1.8 m) from finished floor
Monitoring Area:		7,000 to 10,000 ft ² / 464 to 929 m ² 40 to 56 foot / 12 to 17 meter radius, application dependent
Suggested Alarm Points		Low Alarm: 25 ppm / Mid Alarm: 50 ppm / High Alarm: 100 ppm
Certifications:		CSA-C22.2 No. 205-12, UL508 (Edition 18):2018 EMC Directive 2014/30/EU, EN 50270:2015, Type 1, EN61010 Sensor complies with UL2075, 2 nd Edition RoHS compliant circuit boards This device complies with part 15 of the FCC Rules
Notes:		Never install gas detectors in the direct path of moving air.

Conditions Affecting Electrochemical Sensors:

- Typically designed to operate between -10°C and +50°C, do not exposed to extreme temperatures for prolonged periods of time. Repeated or prolonged exposure to temperatures like 60-65°C / 140-149 can lead to evaporation of the electrolyte and shifts in baselines readings.
- Continuous operation in low relative humidity environments can dry out the electrolyte and extended periods of exposure to high moisture environments can cause the electrolyte to absorb the moisture, causing dilution and inaccurate measurements.
- Prolonged exposure to extremely high gas concentrations can compromise sensor performance.
- Paint fumes, cleaning products, dust, sand, water, insects can reduce lifespan and compromise performance. Avoid exposure to high concentrations of solvent vapours both during storage and operation. Organic solvents may block the sensing electrodes, create false baselines and in some cases damage the electrodes and physically damage the body of the sensor.
- Negative cross-sensitivities may cause the sensor to produce lower readings than the true concentration of gas in ambient air.
- Before initial use after production may be stored at room temperature ideally at 20°C / 68°F and 60%RH or preferably in the fridge for up to 6 months. Beyond this period, the sensor performance is likely to deteriorate, such as with longer response time and lower sensitivity regardless of whether sensor has been used or not.
- The more exotic gases (chlorine, ozone etc.) tend to have shorter life spans than the more common gases (CO, nitrogen dioxide)
- Install gas detector vertically so the display is over top of the sensor vent and device is flat against a wall or column. Never install gas detectors in the direct path of moving air.

In addition to the factors listed above, most sensors will suffer general wear and tear and it may not always be easy to detect the damage caused, making regular maintenance important to help keep the sensors in good working order. Regular maintenance includes inspecting, cleaning if necessary, bump testing and calibration.